

Förreglingstabell för Ljusdal

Ändr. d. 16-10-61. Ed. Dnr 74/53 (Blad 1, 2, 3, 4, 5, 6, 7, 11, 12, 13, 14,
17, 19, 20, 23, 24)

		KUNGL. JÄRNVAGSSTYRELSEN ELEKTROTEKNISKA BYRÅN	
		<u>Ljusdal.</u>	
Andr.			
Rit. <i>Bla</i>	Gr. <i>sen</i>		
Godkänd d. 10/15 54			
<i>Rundberg</i>		Ebrsi 388 002	

L5

1.

Ställare	Med	Fordrar	Om ej
3h		<u>13h</u>	
"	<u>6, 8</u>	37v	44
"	<u>6, 8, 18</u>	33h	<u>40</u>
"	<u>6, 8, 18</u>	33h	40
"	<u>6, 8, 16</u>	33h, 37v	
"	<u>6, 8, 16</u>	37h	38
"	<u>6, 8, 16</u>	<u>21h</u>	
"	<u>6, 8, 16, 22</u>	<u>29h</u>	
		<u>H29h/H29h</u>	
"	<u>6, 8, 16, 22, H29h</u>	Ljr 5L29h	
"	<u>6, 8, 16, 22, H29h</u>	33h, 37v	
"	<u>6, 8, 16, 22, 30, H29h</u>	37h	36, <u>38</u>
"	<u>6, 8, 16, 22, 30, H29h</u>	37h	<u>36, 38</u>
"	<u>6, 8, 16, 22, 24</u>	<u>29h</u>	
		<u>H29h/H29h</u>	
"	<u>6, 8, 16, 22, 24, H29h</u>	Ljr 5L29h	
"	<u>6, 8, 16, 22, 24, H29h</u>	33h, 37v	
"	<u>6, 8, 16, 22, 24, 30, H29h</u>	37h	36, <u>38</u>
"	<u>6, 8, 16, 22, 24, 30, H29h</u>	37h	<u>36, 38</u>
	<u>6, 8, 16, 22, 24</u>	31h	
		<u>H31h/H31h</u>	
"	<u>6, 8, 16, 22, 24, H31h</u>	Ljr 5L31h	
"	<u>6, 8, 16, 22, 24, H31h</u>	33h, 37v	
"	<u>6, 8, 16, 22, 24, 32, H31h</u>	37h	36, <u>38</u>
"	<u>6, 8, 16, 22, 24, 32, H31h</u>	37h	<u>36, 38</u>
3v			

Ställare	Med	Fordrar	Om ej
5h		<u>17h</u>	
"	<u>4,8</u>	37v	44
"	<u>4,8,18</u>	33h	<u>40</u>
"	<u>4,8,18</u>	33h	40
"	<u>4,8</u>	16, 33h, 37v	
"	<u>4,8</u>	37h	38
"	4,24	<u>21h</u>	
"	4,24	{ <u>29h</u>	
		{ <u>H29h/H29h</u>	
"	4,24, <u>H29h</u>	Lj r SL 29h	
"	4,24, H29h	33h, 37v	
"	4,24, 30, H29h	37h	36, <u>38</u>
"	4,24, <u>30</u> , H29h	37h	<u>36, 38</u>
"	4, <u>24</u>	<u>25h</u>	
"	4, <u>24</u>	{ <u>31h</u>	
		{ <u>H31h/H31h</u>	
"	4, <u>24</u> , <u>H31h</u>	Lj r SL 31h	
"	4, <u>24</u> , H31h	33h, 37v	
"	4, <u>24</u> , <u>32</u> , H31h	37h	36, <u>38</u>
"	4, <u>24</u> , 32, H31h	37h	<u>36, 38</u>
5v		—	

Ställare	Med	Fordrar	Om ej
21h		(22), JZan	
"	22	(26)	
"	22, 26	29v	32
"	22, 26	31v	30
"	22, 26	24	
"	22, 26	29v	32
"	22, 26	31v	30
"	22	(24)	
"	22, 24	26	
"	22, 24	29v	32
"	22, 24	31v	30
"	22, 24	25v, 26, 54	
"	22, 24	29v	32
"	22, 24	31v	30
21v		(26)	
"	26	(22), 24	
"	22, 26	53	
"	22, 26,	13h ✓	6
"	22, 26	17h	4
"	22, 26	13h	6/8/16
"	22, 26	17h	4/8/16
"	26	22	
"	26	13h	6/8/16
"	26	17h	4/8/16

Ställare	Med	Fordrar	Om ej
29h		30, 32	
"	30	37v	<u>36/38/44</u>
"	<u>30</u>	31v	
"	<u>30</u>	37v	<u>36/38/44</u>
29v		30, 32	
"	<u>32</u>	25h, 31h	
"	<u>32</u>	21h	22/24
"	32	21h	<u>22, 24</u>

Ställare	Med	Fordrar	Om ej
3/h		30, 32	
"	<u>32</u>	29v	
"	<u>32</u>	37v	36/38/44
"	32	37v	36/38/44
3/v		30 , 32	
"	30	25h	
"	30	21h	22/24
"	<u>30</u>	29h	
"	<u>30</u>	21h	<u>22, 24</u>

Ställare	Med	Fordrar	Om ej
37h		③⑧, 44, 56	
"	38	J Ibs, J IIbs	
"	<u>38</u>	③⑥, J IIIs	
"	36, <u>38</u>	J Ibs	
"	<u>36</u> , <u>38</u>	J IIbs	
37v		④④, 56, J Ibs, J IIbs, J IIIs	
"	44	③⑧	
"	<u>38</u> , 44	③⑥	
"	<u>36</u> , <u>38</u> , 44	29h	30
"	<u>36</u> , <u>38</u> , 44	31h	<u>32</u>
"	36, <u>38</u> , 44	29h	<u>30</u>
"	36, <u>38</u> , 44	31h	32
"	38, 44	13h	6/8/16
"	38, 44	17h	4/8/16
"	<u>44</u>	33h, ④⑩, 55, 57 J IVs, J V s	
"	40, <u>44</u>	13h	8/18
"	40, <u>44</u>	17h	4/8/18
"	<u>40</u> , <u>44</u>	13h	8/18
"	<u>40</u> , <u>44</u>	17h	4/8/18

Ställare	Med	Fordrar	Om ej
45h		—	
45v		<u>37v</u>	
"	<u>36, 38, 44</u>	{ <u>31v</u>	
		{ <u>H31v/H31v</u>	
"	<u>36, 38, 44, H31v</u>	LjrsL 31v	
"	<u>30, 36, 38, 44, H31v</u>	54	
"	<u>30, 36, 38, 44, H31v</u>	21h	
"	<u>30, 36, 38, 44, H31v</u>	25v	22
"	<u>36, 38, 44</u>	{ <u>29v</u>	
		{ <u>H29v/H29v</u>	
"	<u>36, 38, 44, H29v</u>	LjrsL 29v	
"	<u>32, 36, 38, 44, H29v</u>	54	
"	<u>32, 36, 38, 44, H29v</u>	21h	
"	<u>32, 36, 38, 44, H29v</u>	25v	22
"	<u>38, 44</u>	9v, 13h	
"	<u>38, 44</u>	13v	16
"	<u>38, 44</u>	17h	4
"	<u>38, 44</u>	17v	6
"	<u>44</u>	13h	8
"	<u>44</u>	17h	4/8
"	<u>40, 44</u>	9v	18
"	<u>40, 44</u>	9v	<u>18</u>

Ställare	Fordrar	Om ej
16	13v	
	13h	<u>6/8</u>
	17h	<u>4/8</u>
18	9v	
	13h	8
	17h	<u>4/8</u>
22	21h/v, 25h/v	
24	25h/v	
	21h	22, <u>26</u>
	21v	<u>26</u>

Ställare	Fordrar	Om ej
26	21h/v, 25h/v	
	37h	38
"	37v	38/44

Ställare	Fordrar	Om ej
38	37H	
"	37V	<u>44</u>
40	33H	
"	37V	44
44	33H, 37H/V	

Relä	Fordrar	Om ej
50	9v	
"	13h	8
"	17h	4/8
51	9v, 13h/v	
"	17h	4
"	17v	6
52	9v, 13v	
"	13h	<u>6</u>
"	17h	4
53	17v	
"	13h	6
"	17h	<u>4</u>
"	21v	<u>22/26</u>
"	25v	<u>22</u>

Rela ^o	Fordrar	Om ej
54	25h/v, JIam	
•	21h	22/24
55	33h	
•	37v	44
56	33h, 37h/v	
57	33h	
•	37v	44

Relö"	Med	Fordrar	Om ej
Jias		(24)	
"	<u>24</u>	(22)	
"	<u>22, 24</u>	(16)	
"	<u>16, 22, 24</u>	(8)	
"	<u>8, 16, 22, 24</u>	3h	
"	<u>22, 24</u>	(6)	
"	<u>6, 22, 24</u>	(4)	
"	<u>4, 6, 22, 24</u>	5h	
"	<u>6, 22, 24</u>	3h	
Jibs		(30)	
"	<u>30</u>	Jias/Ljr SL29h	
"	<u>30</u>	Jias/Ljr SL31h	
Jias		(26)	
"	<u>26</u>	(22)	
"	<u>22, 26</u>	(16)	
"	<u>16, 22, 26</u>	(8)	
"	<u>8, 16, 22, 26</u>	3h	
"	<u>26</u>	(22)	
"	<u>22, 26</u>	(16)	
"	<u>16, 22, 26</u>	(8)	
"	<u>8, 16, 22, 26</u>	3h	
"	<u>22, 26</u>	(6)	
"	<u>6, 22, 26</u>	(4)	
"	<u>4, 6, 22, 26</u>	5h	
"	<u>6, 22, 26</u>	3h	

Rela ⁿ	Med	Fordrar	Om ej
J ^{II} bs		(32)	
"	32	J ^{II} as/Ljr SL29H	
"	<u>32</u>	J ^I as/Ljr SL31H	
J ^{III} s		(16)	
"	16	(8)	
"	8,16	(6)	
"	6,8,16	(4)	
"	4,6,8,16	3h	
"	<u>4</u> ,6,8,16	5h	
J ^{IV} s		(18)	
"	18	(8)	
"	<u>8</u> ,18	(6)	
"	6, <u>8</u> ,18	(4)	
"	4,6, <u>8</u> ,18	3h	
"	<u>4</u> ,6, <u>8</u> ,18	5h	
J ^V s		(18)	
"	<u>18</u>	(8)	
"	<u>8</u> ,18	(6)	
"	6, <u>8</u> ,18	(4)	
"	<u>4</u> ,6, <u>8</u> , <u>18</u>	3h	
"	<u>4</u> ,6, <u>8</u> , <u>18</u>	5h	

Rela ⁿ	Med	Fordrar	Om ej
JIbn		③⑥	
"	<u>36</u>	③⑧	
"	<u>36, 38</u>	④④	
"	<u>36, 38, 44</u>	45v	
JIan		③②	
"	32	JIbn/LjrSL31v	
"	<u>32</u>	JIbn/LjrSL29v	
JIIbn		③⑥	
"	36	③⑧	
"	<u>36, 38</u>	④④	
"	<u>36, 38, 44</u>	45v	
JIIan		③①	
"	30	JIbn/LjrSL31v	
"	<u>30</u>	JIIbn/LjrSL29v	
JIIIbn		③⑧	
"	38	④④	
"	<u>38, 44</u>	45v	

Rela ⁿ	Med	Fordrar	Omej
JIVn		(40)	
"	40	(44)	
"	40,44	45v	
JIVn		(40)	
"	<u>40</u>	(44)	
"	<u>40.44</u>	45v	

Relá	Med	Fordrar	Omei
09v		9v, <u>L8,18</u>	
"		13h	8
"		17h	4/8
013h		9v, 13h/v, <u>L4,6</u>	
"		17h	4
"		21v	6, 8/6, 16/6, 22, 26/6, <u>22/6, 26</u>
"		25v	6, 8/6, 16/6, 22/6, <u>22</u>
013v		9v, 13h/v, <u>L16</u>	
"		17h	4
017h		17h/v, <u>L4,6</u>	
"		9v, 13v	4
"		13h	6
"		21v	4, 22, 26/4, 8/4, 16/4, 22/4, <u>26</u>
"		25v	4, 22/4, 8/4, 16/4, <u>22</u>
017v		17h/v, <u>L4,6</u>	
"		9v, 13v	4
"		13h	6
021h		21h/v, <u>L22, 24, 26</u>	
"		25v	22

Ls

24

Relä#	Med	Fordrar	Om ej
021v		21h/v, <u>L22,24,26</u>	
"		13h	6,8/6,16/6,22,26/6,22/6,26
"		17h	4,8/4,16/4,22,26/4,22/4,26
"		25v	22
021/25h		25h/v, <u>L22,24,26</u>	
"		21h/v	22,24,26
025v		25h/v	
"		<u>L22,24,26</u> / t025v	
"	<u>L22,24,26</u>	13h	6,8/6,16/6,22/6,22/24
"	<u>L22,24,26</u>	17h	6,8/6,16/6,22/6,22/24
"	<u>L22,24,26</u>	21h	22/24
"	t025v	24	
029h		29h/v, <u>L30,32</u>	
"		31h/v	30,32
031h/v		31h/v, <u>L30,32</u>	
"		29h/v	30,32
033h		33h, <u>L40,44</u>	
"		37v	44
037h		33h, 37h/v, <u>L36,38</u>	
037v		33h, 37h/v, <u>L40,44</u>	